

This update applies to the Operator Reference (Bulletin MN06091L Issue/Rev. 0.2 (1/96)) for all AccuLoad IIs operating with AccuLoad-RBM Revision 17 and above firmware.

System Parameter 285

The AccuLoad II-RBM can be configured to inhibit the activation of the product pump for the clean line product until the start of the clean line phase of the delivery.

System Parameter 285, Clean Line Pump Start Volume, allows the entry of the remaining volume at the point in the delivery process when the pump for the clean line product is to be activated. This volume is in addition to the clean line volume to be delivered. If the Clean Line Pump Start Volume is set to zero, the pump for the clean line product will be turned on at the start of the batch.

Fatal: Entry is out of specified range.

The specifications contained herein are subject to change without notice and any user of said specifications should verify from the manufacturer that the specifications are currently in effect. Otherwise, the manufacturer assumes no responsibility for the use of specifications which may have been changed and are no longer in effect.

Headquarters:

6677 North Gessner Road, Houston, TX 77040 USA, Phone: 713/510-6970, Fax: 713/510-6972

Locations:

Erie, PA USA Phone 814/898-5000, Fax 814/899-8927

Corpus Christi, TX USA Phone 361/289-3400, Fax 361/289-1115

Caldwell, TX USA Phone 979/567-1693, Fax 979/567-0480

Longmont, CO USA Phone 303/702-7400, Fax 303/702-1608

Los Angeles, CA USA Phone 661/296-7711, Fax 661/296-5166

Eunice, LA USA Phone 337/550-7133, Fax 337/550-7134

Thetford, England Phone (44) 1842-82-2900, Fax (44) 1842-76-5402

Slough, England Phone (44) 1753-57-1515, Fax (44) 1753-52-9966

Ellerbek, Germany Phone (49) 4101-3040, Fax (49) 4101-304133

Kongsberg, Norway Phone (47) 32/286-700, Fax (47) 32/289-590

Barcelona, Spain Phone (34) 93/201-0989, Fax (34) 93/201-0576

Moscow, Russia Phone (7) 095/564-8705, Fax (7) 095/926-5066

Melbourne, Australia Phone (61) 3/9807-2818, Fax (61) 3/9807-2816

Beijing, China Phone (86) 10/6500-2251, Fax (86) 10/6512-6857

Chennai, India Phone (91) 44/450-4400, Fax (91) 44/450-2114

San Juan, Puerto Rico Phone 787/274-3760, Fax 787/274-1020

Caracas, Venezuela Phone (58) 212/952-8417, Fax (58) 212/952-5191

Visit our website at www.fmcmeasurementsolutions.com